

Symbol	Stock No	Drawing No	Description
			0 COMMODORE COLOR MONITOR 1702
CRT1			SOCKET, CRT
C1202	436924		.47UF 10% 35V TANTALUM
C1204			3.3UF 50V ELECTROLYTIC NP
C1308			TRIMMER
C1342	151501		10UF 16V ELECTROLYTIC
C1351	146317		4.7UF +50% -10% 250V ELECTROLYTIC
C1352	120696		1000PF 10% 3000V CERAMIC
C1356	146317		4.7UF +50% -10% 250V ELECTROLYTIC
C1402	150832		2.2UF 20% 16V TANTALUM
C1404	160134		0.1 UF +- 5% 50V FILM
C1406	443266		.056UF 1% 50V FILM
C1423	147038		100UF 35V ELECTROLYTIC
C1425	154386		470UF +100% -10% 35V ELECTROLYTIC
C1426			.15UF 50V
C1502	152141		220UF 35V ELECTROLYTIC
C1508			5600PF 100V POLYPROPYLENE
C1523	158752		33UF 160V ELECTROLYTIC
C1526			5000PF 1600V METAL-POLYPROPYLENE
C1529			.53UF 200V METAL-POLYPROPYLENE
C1530	146536		2.2UF 50V ELECTROLYTIC
C1531	150334		470UF 25V ELECTROLYTIC
C1534			1500PF 1600V METAL-POLYPROPYLENE
C1535	451791		.082UF 10% 100V FILM
C1541	144662		1UF 160V ELECTROLYTIC
C1551	144925		1000UF 20% 16V ELECTROLYTIC
C1901	106547		4700PF 10% 500V CERAMIC
C1902	106547		4700PF 10% 500V CERAMIC
C1903	106547		4700PF 10% 500V CERAMIC
C1904			470UF 20% 200V ELECTROLYTIC
C1906	158952		.1 UF 20% 100V FILM
C1907	442264		10UF 160V ELECTROLYTIC
C1908	158952		.1 UF 20% 100V FILM
C1910			.1UF CERAMIC
C1911			.1UF CERAMIC
D1201	153493		DIODE - TYPE 1SS133
D1202	150071		DIODE - TYPE W06B
D1204	153493		DIODE - TYPE 1SS133
D1301	442098		DIODE - TYPE 1S1555
D1302	153493		DIODE - TYPE 1SS133
D1351			DIODE - TYPE RM-2C
D1401			DIODE - TYPE MA4110(M)
D1421			DIODE - TYPE 1SR124-400
D1422			DIODE - TYPE 1SR124-400
D1501			DIODE - TYPE MA4110(M)
D1502	158313		DIODE - TYPE 1SS81
D1503	153493		DIODE - TYPE 1SS133
D1504			DIODE - BRIDGE 1B4B42

Symbol	Stock No	Drawing No	Description
Q1501	154197		TRANSISTOR - TYPE 2SA1015
Q1521			TRANSISTOR - TYPE 2SC1627A
Q1522			TRANSISTOR - TYPE 2SD1426
R01			280 OHM 10% 20W (NONFLAM)
R1209			1000 OHM VARIABLE (SUB CONTRAST)
R1303			50000 OHM VARIABLE (SUB COLOR)
R1305			20000 OHM VARIABLE (SUB TINT)
R1352			5000 OHM VARIABLE (BLUE CUT OFF)
R1354			5000 OHM VARIABLE (RED CUT OFF)
R1356			5000 OHM VARIABLE (GREEN CUT OFF)
R1357	832312		12000 OHM 2% 2W FILM FP
R1358			12000 OHM 2% 2W FILM FP
R1359			12000 OHM 2% 2W FILM FP
R1360	502233		3300 OHM CARBON COMP
R1361	502233		3300 OHM CARBON COMP
R1362			3300 OHM CARBON COMP
R1369			200 OHM VARIABLE (RED DRIVE)
R1371			200 OHM VARIABLE (GREEN DRIVE)
R1378			270 OHM 10% ZINC
R1406			200 OHM VARIABLE (V LINEARITY)
R1408			200 OHM VARIABLE (V HEIGHT)
R1414	433904		100 OHM 1% 1W FILM
R1421	832A15		1.5 OHM 5% 2W FILM FP
R1429			500 OHM VARIABLE (V POSITION)
R1504			5000 OHM VARIABLE (H. FREQ)
R1511	831056		56 OHM 2% 1W FILM FP
R1523	438981		1000 OHM 1% 1W FILM
R1526	433780		1000 OHM 1% 1/2W FILM
R1530	831012		12 OHM 2% 1W FILM
R1531	451470		47 OHM 5% 2W FILM
R1532	433780		1000 OHM 1% 1/2W FILM
R1534	831147		470 OHM 2% 1W FILM FP
R1551	831A27		2.7 OHM 5% 1W FILM FP
R1607	831A56		5.6 OHM 2% 1W FILM FP
R1701	144096		33 OHM 5% 1W FILM
R1702	157212		20000 OHM 1% 1/4W FILM
R1705	433929		14000 OHM 1% 1/4W FILM
R1854			10000 OHM VARIABLE (CONTRAST)
R1860			10000 OHM VARIABLE (BRIGHTNESS)
R1863			4700 OHM VARIABLE (SUB BRIGHT)
R1866			10000 OHM VARIABLE (TINT)
R1869			10000 OHM VARIABLE (COLOR)
R1871			10000 OHM VARIABLE (VOLUME)
R1875			10000 OHM VARIABLE (VERT HOLD)
R1877			1000 OHM VARIABLE (H. POSITION)
R1902			2 OHM 7W (NON FLAM)
R1907	832A47		4.7 OHM 2% 2W FILM FP
R1910	445918		6800000 OHM 10% 1/2W FILM
S01			SWITCH, POWER
S1201			SWITCH, SERVICE

Symbol	Stock No	Drawing No	Description
			0 COMMODORE COLOR MONITOR 1701
C1202	150852		.47UF 20% 35V TANTALUM
C1204			3.3UF 20% 50V ELECTROLYTIC (NP)
C1351	151501		10UF 16V ELECTROLYTIC
C1402	150832		2.2UF 20% 16V TANTALUM
C1407	152239		3.3UF 50V ELECTROLYTIC
C1411	150146		100UF 160V ELECTROLYTIC
C1412	150143		3.3UF 160V ELECTROLYTIC
C1508			5600PF 5% 50V POLYPROPYLENE
C1511	461263		47UF 20% 160V ELECT
C1512			1500PF 5% 1600V MET-POLYPROP
C1513			1500PF 5% 1600V MET-POLYPROP
C1514			1500PF 5% 1600V MET-POLYPROP
C1515			.53UF 5% 200V MET-POLYPROP
C1520			1UF +30% -10% 160V ELECTROLYTIC
C1522			510PF 5% 1600V MET-POLYPROP
C1523	144662		1UF 160V ELECTROLYTIC
C1530			510PF 5% 1600V MET-POLYPROP
C1531			1500PF 5% 1600V MET-POLYPROP
C1610	152240		.47UF 50V ELECTROLYTIC
C1612	442264		10UF 160V ELECTROLYTIC
C1613	442264		10UF 160V ELECTROLYTIC
C3101	210137		10UF 50% 250V ELECTROLYTIC
C3102	120696		1000PF 10% 3000V CERAMIC
C9104			330UF +30% -10% 200V ELECTROLYTIC
C9105			10UF +50% -10% 250V ELECTROLYTIC
C9107			330UF +30% -10% 200V ELECTROLYTIC
C9108	144662		1UF 160V ELECTROLYTIC
C9701	157260		.047UF 20% 125V FILM
C9702	157260		.047UF 20% 125V FILM
CRT-1			SOCKET - CRT
D1201	150177		DIODE - TYPE 1S2471B
D1202	150071		DIODE - TYPE W06B
D1203	150071		DIODE - TYPE W06B
D1301	147218		DIODE - TYPE 1S2473YE
D1302	147218		DIODE - TYPE 1S2473YE
D1401	147218		DIODE - TYPE 1S2473YE
D1402	152742		DIODE - TYPE RD11EB
D1405	452627		DIODE - TYPE RD3.6EB
D1503	458267		DIODE - TYPE RH1
D1504			DIODE - TYPE V19E
D1505	152742		DIODE - TYPE RD11EB
D1506	150528		DIODE - TYPE W06A
D1507	150074		DIODE - TYPE V09G
D1508	147218		DIODE - TYPE 1S2473YE
D1601	149434		DIODE - TYPE MA26WD
D1701	154857		DIODE - TYPE HZ201
D9101			DIODE - TYPE 1S1887A

Symbol	Stock No	Drawing No	Description
R1511	243532		8200 OHM 5% 2W FILM
R1512	243532		8200 OHM 5% 2W FILM
R1514	832168		680 OHM 2% 2W FILM FP
R1515	831A82		8.2 OHM 2% 1W FILM FP
R1522	449226		4.7 OHM 5% 1W FILM
R1523	832018		18 OHM 2% 2W FILM
R1524			4700 OHM LINEAR VARIABLE
R1528	239933		390 OHM 5% 1W FILM
R1532	454161		270 OHM 10% ZINC
R1703	148846		41200 OHM 1% 1/2W FILM
R1704	161294		9530 OHM 1% 1/2W FILM
R3102			5000 OHM VARIABLE (BLUE)
R3104			5000 OHM VARIABLE (RED)
R3106			5000 OHM VARIABLE (GREEN)
R3109			220 OHM VARIABLE (RED)
R3111			220 OHM VARIABLE (GREEN)
R3112	832312		12000 OHM 2% 2W FILM FP
R3113	832312		12000 OHM 2% 2W FILM FP
R3114	832312		12000 OHM 2% 2W FILM FP
R3115	502233		3300 OHM 5% 1/2W COMP.
R3116	502247		4700 OHM 5% 1/2W COMP.
R3117	502233		3300 OHM 5% 1/2W COMP.
R4003			10000 OHM VARIABLE (TINT)
R4004			10000 OHM VARIABLE (COLOR)
R4006			10000 OHM VARIABLE (CONTRAST)
R4012			10000 OHM VARIABLE (BRIGHTNESS)
R4015			10000 OHM VARIABLE (VERT HOLD)
R4016			500 OHM VARIABLE (HOR POSITION)
R4022			4700 OHM VARIABLE (SUB BRIGHT)
R4024			200000 OHM VARIABLE (VOLUME)
R9101			POSITOR
R9103			4.7 OHM 5% 3W FILM
R9104			10000 OHM 5% 2W FILM
R9105	229927		18000 OHM 5% 1W FILM
R9108	143573		47000 OHM 1% 1/2W FILM
R9109			2000 OHM VARIABLE (LINEAR B)
R9110	444794		3010 OHM 1/4W FILM
S01			SWITCH, POWER
S1201			SWITCH, SERVICE
SP01	432722		3IN 8 OHM 1W PLAIN CONE
T01			TRANSFORMER, POWER
T502			HV MODULE
T1201			TRANSFORMER, TRAP 3.58
T1301			TRANSFORMER, BP 3.58
T1501			TRANSFORMER, HOR. DRIVE
T1503			TRANSFORMER, SIDE PIN
T1602			TRANSFORMER, SOT
V01			PICTURE TUBE - TYPE 370FVB22(E)
*V01			PICTURE TUBE - TYPE 370ESB22(E)

Symbol	Stock No	Drawing No	Description
			0 COMMODORE C64 COMPUTER
			PCB ASSEMBLY #326298
C1	157811		100000PF 5% 50V CERAMIC Z5U
C2	157811		100000PF 5% 50V CERAMIC Z5U
C3	157811		100000PF 5% 50V CERAMIC Z5U
C4	458419		470000PF 20% 50V CERAMIC
C5	458419		470000PF 20% 50V CERAMIC
C6	458419		470000PF 20% 50V CERAMIC
C7	458419		470000PF 20% 50V CERAMIC
C8	160397		10 UF 25V ELECT
C9	458419		470000PF 20% 50V CERAMIC
C10	462159		470PF 1% 50V CERAMIC
C11	462159		470PF 1% 50V CERAMIC
C12	160397		10 UF 25V ELECT
C13	160397		10 UF 25V ELECT
C14	160397		10 UF 25V ELECT
C15	160397		10 UF 25V ELECT
C16	157811		100000PF 5% 50V CERAMIC Z5U
C17	160397		10 UF 25V ELECT
C18	157811		100000PF 5% 50V CERAMIC Z5U
C19	436807		2200UF 16V ELECTROLYTIC
C20	157209		.22UF 5% 100V FILM
C21	157209		.22UF 5% 100V FILM
C22	157811		100000PF 5% 50V CERAMIC Z5U
C23	462076		360PF 1% 50V CERAMIC NPO
C24	160397		10 UF 25V ELECT
C25	462165		220000PF 5% 50V CERAMIC X7R
C26	462165		220000PF 5% 50V CERAMIC X7R
C27	462165		220000PF 5% 50V CERAMIC X7R
C28	462165		220000PF 5% 50V CERAMIC X7R
C29	458419		470000PF 20% 50V CERAMIC
C30	157811		100000PF 5% 50V CERAMIC Z5U
C31	157811		100000PF 5% 50V CERAMIC Z5U
C32	157811		100000PF 5% 50V CERAMIC Z5U
C33	458419		470000PF 20% 50V CERAMIC
C34	160397		10 UF 25V ELECT
C35	157811		100000PF 5% 50V CERAMIC Z5U
C36	462150		20PF 50V CERAMIC NPOTOL+- .5PF
C37	462048		1000PF 500V MICA
C38	462128		51PF 1% 50V CERAMIC NPO
C39	157811		100000PF 5% 50V CERAMIC Z5U
C40	462165		220000PF 5% 50V CERAMIC X7R
C41	462165		220000PF 5% 50V CERAMIC X7R
C42	462165		220000PF 5% 50V CERAMIC X7R
C43	462165		220000PF 5% 50V CERAMIC X7R
C44	458419		470000PF 20% 50V CERAMIC
C45	157811		100000PF 5% 50V CERAMIC Z5U
C46	157811		100000PF 5% 50V CERAMIC Z5U

Symbol	Stock No	Drawing No	Description
C103	157811		100000PF 5% 50V CERAMIC Z5U
C105	157811		100000PF 5% 50V CERAMIC Z5U
CN1			HEADER ASSEMBLY 20PIN
CN4			SOCKET DIN 6PIN
CN5			SOCKET DIN 5PIN
CN6			CONNECTOR, CARD EDGE 44PIN
CN7			CONNECTOR, DIN 7PIN
CN8			PLUG ASSEMBLY 9PIN RT ANGLE
CN9			PLUG ASSEMBLY 9PIN RT ANGLE
CN10			HEADER ASSEMBLY 3PIN
CR1	428918		DIODE - TYPE 1N4371A
CR2	230018		DIODE - TYPE 1N755
CR3	229936		DIODE - TYPE 1N914
CR4			DIODE - BRIDGE VM08
CR5	426115		DIODE - TYPE 1N4001
CR6	426115		DIODE - TYPE 1N4001
F1	427745		FUSE - 1 1/2 AMP 250 V
FB1			FERRITE BEAD
FB2			FERRITE BEAD
FB3			FERRITE BEAD
FB4			FERRITE BEAD
FB5			FERRITE BEAD
FB6			FERRITE BEAD
FB7			FERRITE BEAD
FB8			FERRITE BEAD
FB9			FERRITE BEAD
FB10			FERRITE BEAD
FB11			FERRITE BEAD
FB12			FERRITE BEAD
FB13			FERRITE BEAD
FB14			FERRITE BEAD
FB15			FERRITE BEAD
FB16			FERRITE BEAD
FB17			FERRITE BEAD
FB18			FERRITE BEAD
FB19			FERRITE BEAD
FB20			FERRITE BEAD
FB21			FERRITE BEAD
FB22			FERRITE BEAD
FB23			FERRITE BEAD
L1			COIL - 2.2UH
L2			COIL - 2.2UH
L3			COIL - 3.0UH
L4			COIL - LINE FILTER ASSEM
L5			COIL - 1.2UH
M1			MODULATOR

Symbol	Stock No	Drawing No	Description
RP4			3300 OHM RESISTOR ARRAY 10PIN
SW1			SWITCH DPDT (ROCKER)
U1			IC - TYPE 6526 CIA
U2			IC - TYPE 6526 CIA
U3			IC - TYPE 2364 (BASIC ROM)
U4			IC - TYPE 2364 (KERNAL ROM)
U5			IC - TYPE 2332 (CHARACTER ROM)
U6			IC - TYPE 2114L-30 (RAM)
U7			IC - TYPE 6510 (PROCESSOR)
U8	422259		IC - TYPE SN7406J
*UB	433669		IC - TYPE SN7416
U9			IC - TYPE 4164 (200 NS)
U10			IC - TYPE 4164 (200 NS)
U11			IC - TYPE 4164 (200 NS)
U12			IC - TYPE 4164 (200 NS)
U13	456363		IC - TYPE SN74LS257N
U14	444957		IC - TYPE SN74LS258N
U15	437738		IC - TYPE SN74LS139N
U16	451411		IC - TYPE CD4066BE
U17			IC - TYPE 825100 (PLA)
U18			IC - TYPE 6581 (SID)
U19			IC - TYPE 6567 (VIC IT)
U20	443942		IC - TYPE LM556CN
U21			IC - TYPE 4164 (200 NS)
U22			IC - TYPE 4164 (200 NS)
U23			IC - TYPE 4164 (200 NS)
U24			IC - TYPE 4164 (200 NS)
U25	456363		IC - TYPE SN74LS257N
U26	449130		IC - TYPE SN74LS373N
U27	437613		IC - TYPE SN74LS08N
U28	451411		IC - TYPE CD4066BE
U29	451516		IC - TYPE SN74LS74AN
U30	433394		IC - TYPE SN74LS193N
U31	454336		IC - TYPE SN74LS629N
U32	433764		IC - TYPE MC4044P
VR1	453984		IC - TYPE MC7812CT
VR2	434637		IC - TYPE MC7805CT
Y1			CRYSTAL 14.31818 MHZ
1			CONNECTOR PANEL (JOYSTICK)
2			CARTRIDGE GUIDE
3			SHIELD BOX
4			SHIELD CAP
			PCB ASSEMBLY #250407-04

Symbol	Stock No	Drawing No	Description
C54	157811		100000PF 5% 50V CERAMIC Z5U
C55	157811		100000PF 5% 50V CERAMIC Z5U
C56	157811		100000PF 5% 50V CERAMIC Z5U
C57	160397		10 UF 25V ELECT
C58	157811		100000PF 5% 50V CERAMIC Z5U
C59	157811		100000PF 5% 50V CERAMIC Z5U
C60	157811		100000PF 5% 50V CERAMIC Z5U
C62	160397		10 UF 25V ELECT
C65	160397		10 UF 25V ELECT
C66	157811		100000PF 5% 50V CERAMIC Z5U
C67	157811		100000PF 5% 50V CERAMIC Z5U
C68	157811		100000PF 5% 50V CERAMIC Z5U
C70			16PF 5% FILM
C74	157811		100000PF 5% 50V CERAMIC Z5U
C82	157811		100000PF 5% 50V CERAMIC Z5U
C83	462072		82PF 1% 50V CERAMIC NPO
C84	157811		100000PF 5% 50V CERAMIC Z5U
C85	458419		470000PF 20% 50V CERAMIC
C88			1000UF 25V ELECTROLYTIC
C89	157811		100000PF 5% 50V CERAMIC Z5U
C90	459595		470UF 50V ELECT (AXIAL LEAD)
C91	152220		100UF 16V ELECTROLYTIC
C92	157811		100000PF 5% 50V CERAMIC Z5U
C93	462169		1800PF 1% 100V CERAMIC NPO
C94	160397		10 UF 25V ELECT
C95	157811		100000PF 5% 50V CERAMIC Z5U
C96	157811		100000PF 5% 50V CERAMIC Z5U
C97	462165		220000PF 5% 50V CERAMIC X7R
C98	162276		0.1 UF 80-20% 50V DISC
C99	162276		0.1 UF 80-20% 50V DISC
C100	462165		220000PF 5% 50V CERAMIC X7R
C101	162276		0.1 UF 80-20% 50V DISC
C102	160397		10 UF 25V ELECT
C103	157811		100000PF 5% 50V CERAMIC Z5U
C105	157811		100000PF 5% 50V CERAMIC Z5U
C108	160397		10 UF 25V ELECT
C200	157811		100000PF 5% 50V CERAMIC Z5U
CN1			HEADER ASSEMBLY 20PIN
CN4			SOCKET DIN 6PIN
CN5			SOCKET DIN 8PIN
CN6			CONNECTOR, CARD EDGE 44PIN
CN7			CONNECTOR, DIN 7PIN
CN8			PLUG ASSEMBLY 9PIN (MINID)
CN9			PLUG ASSEMBLY 9PIN (MINID)
CN10			HEADER ASSEMBLY 3PIN
CR1	428918		DIODE - TYPE 1N4371A
CR2	230018		DIODE - TYPE 1N755
CR4			DIODE - BRIDGE S2VB10
CR5	426115		DIODE - TYPE 1N4001
CR6	426115		DIODE - TYPE 1N4001



Symbol	Stock No	Drawing No	Description
R34	442247		47000 OHM 1% 1/4W FILM
R35	451789		470000 OHM 2% 1/4W FILM
R36	151316		1000 OHM 1% 1/4W FILM
R37	442225		2700 OHM 1% 1/4W FILM
R38	151316		1000 OHM 1% 1/4W FILM
R39	442211		390 OHM 1% 1/4W FILM
R41	435056		1000000 OHM +/- 1% 1/4W FILM
R42	453252		82 OHM 1% 1/4W FILM
R43	442227		3300 OHM 1% 1/4W FILM
R44	442227		3300 OHM 1% 1/4W FILM
R45	442227		3300 OHM 1% 1/4W FILM
R50	435056		1000000 OHM 1% 1/4W FILM
R51	419997		1500 OHM 1% 1/4W FILM
R52	442209		300 OHM 1% 1/4W FILM
R53	442211		390 OHM 1% 1/4W FILM
R100	151316		1000 OHM 1% 1/4W FILM
R101	249262		22000 OHM 2% 1/4W FILM
RP1			33 OHM RESISTOR ARRAY 8PIN
RP2			33 OHM RESISTOR ARRAY 8PIN
RP3			3300 OHM RESISTOR ARRAY 8PIN
RP4			3300 OHM RESISTOR ARRAY 10PIN
SW1			SWITCH DPDT (ROCKER)
U1			IC - TYPE 6526 CIA
U2			IC - TYPE 6526 CIA
U3			IC - TYPE 2364 (BASIC ROM)
U4			IC - TYPE 2364 (KERNAL ROM)
U5			IC - TYPE 2332 (CHARACTER ROM)
U6			IC - TYPE 2114L-20 (RAM)
U7			IC - TYPE 6510 (PROCESSOR)
U8	422259		IC - TYPE SN7406J
*U8	433669		IC - TYPE SN7416N
U9			IC - TYPE 4164 (200NS)
U10			IC - TYPE 4164 (200NS)
U11			IC - TYPE 4164 (200NS)
U12			IC - TYPE 4164 (200NS)
U13	456363		IC - TYPE SN74LS257N
U14	444957		IC - TYPE SN74LS258N
U15	437738		IC - TYPE SN74LS139N
U16	451411		IC - TYPE CD4066BE
U17			IC - TYPE 825100 (PLA)
U18			IC - TYPE 6581 (SID)
U19			IC - TYPE 6567 (VIC II)
U20	443942		IC - TYPE LM556CN
U21			IC - TYPE 4164 (200 NS)
U22			IC - TYPE 4164 (200 NS)
U23			IC - TYPE 4164 (200 NS)
U24			IC - TYPE 4164 (200 NS)
U25	456363		IC - TYPE SN74LS257N
U26	449130		IC - TYPE SN74LS373N
U27	437613		IC - TYPE SN74LS08N

Symbol	Stock No	Drawing No	Description
C48			1800PF 10% 50V CERAMIC
C50	157811		100000PF 5% 50V CERAMIC Z5U
C51	157811		100000PF 5% 50V CERAMIC Z5U
C53	157811		100000PF 5% 50V CERAMIC Z5U
C59	157811		100000PF 5% 50V CERAMIC Z5U
C88			1000UF 25V ELECTROLYTIC
C90	459595		470UF 50V ELECT (AXIAL LEAD)
C91	152220		100UF 16V ELECTROLYTIC
C93			1800PF 10% 50V CERAMIC
C101	162276		0.1 UF 80-20% 50V DISC
C102	157811		100000PF 5% 50V CERAMIC Z5U
C150	462159		470PF 10% 50V CERAMIC
C151	462159		470PF 10% 50V CERAMIC
C152	462159		470PF 10% 50V CERAMIC
C153	462118		68PF 1% 50V CERAMIC NPO
C154	462159		470PF 10% 50V CERAMIC
C200	157811		100000PF 5% 50V CERAMIC Z5U
C204	462083		150PF 1% 50V CERAMIC NPO
C205	462079		220PF 1% 50V CERAMIC NPO
CN1			HEADER ASSEMBLY 20PIN
CN4			SOCKET DIN 6PIN
CN5			SOCKET DIN 8PIN
CN6			CONNECTOR, CARD EDGE 44PIN
CN7			CONNECTOR, DIN 7PIN
CN8			PLUG ASSEMBLY 3PIN
CN9			PLUG ASSEMBLY 3PIN
CN10			HEADER ASSEMBLY 3PIN
CR1	428918		DIODE - TYPE 1N4371A
CR2	425272		DIODE - TYPE 1N754A
CR4			DIODE - BRIDGE S2V310
*CR4			DIODE - BRIDGE DBA20B
*CR4			DIODE - BRIDGE DBA20C
CR5	426115		DIODE - TYPE 1N4001
CR6	426115		DIODE - TYPE 1N4001
CR9	424863		DIODE - TYPE 1N4148
CR12	229936		DIODE - TYPE 1N914
CR13	229936		DIODE - TYPE 1N914
CR14	229936		DIODE - TYPE 1N914
CR15	229936		DIODE - TYPE 1N914
CR16	229936		DIODE - TYPE 1N914
CR100	229936		DIODE - TYPE 1N914
CR101	229936		DIODE - TYPE 1N914
CR102	229936		DIODE - TYPE 1N914
CR103	229936		DIODE - TYPE 1N914
CR104	229936		DIODE - TYPE 1N914
CR105	229936		DIODE - TYPE 1N914
CT1			40PF TRIMMER
F1	427745		FUSE - 1 1/2 AMP 250 V

Symbol	Stock No	Drawing No	Description
*U8	433669		IC - TYPE SN7416N
U9			IC - TYPE 4164 (200 NS)
U10			IC - TYPE 4164 (200 NS)
U11			IC - TYPE 4164 (200 NS)
U12			IC - TYPE 4164 (200 NS)
U13	456363		IC - TYPE SN74LS257N
U14	444957		IC - TYPE SN74LS258N
U15	437738		IC - TYPE SN74LS139N
U16	451411		IC - TYPE CD4066BE
U17			IC - TYPE 825100 (PLA)
U18			IC - TYPE 6581 (SID)
U19			IC - TYPE 6567 (VIC II)
U20	443942		IC - TYPE LM556CN
U21			IC - TYPE 4164 (200 NS)
U22			IC - TYPE 4164 (200 NS)
U23			IC - TYPE 4164 (200 NS)
U24			IC - TYPE 4164 (200 NS)
U25	456363		IC - TYPE SN74LS257N
U26	449130		IC - TYPE SN74LS373N
U27	437613		IC - TYPE SN74LS08N
U28	451411		IC - TYPE CD4066BE
U31			IC - TYPE 7701/8701
VR1	453984		IC - TYPE MC7812CT
VR2	434637		IC - TYPE MC7805CT
Y1			CRYSTAL 16.31818 MHZ
			ALL SYMBOL NUMBERS PREFACED BY AN ASTERISK (*) ARE SUBS-

Symbol	Stock No	Drawing No	Description
			0 COMMODERE DISK DRIVE MODEL 1540/1541
			PCB ASSEMBLY #1540001
C1	158986		1UF 25V ELECTROLYTIC
C2	152267		47UF 16V ELECTROLYTIC
C3	157811		100000PF 5% 50V CERAMIC Z5U
C4	158986		1UF 25V ELECTROLYTIC
C5	152267		47UF 16V ELECTROLYTIC
C6	157811		100000PF 5% 50V CERAMIC Z5U
C7	157811		100000PF 5% 50V CERAMIC Z5U
C8	157811		100000PF 5% 50V CERAMIC Z5U
C9	157811		100000PF 5% 50V CERAMIC Z5U
C10	462118		68PF 1% 50V CERAMIC NPO
C11	157811		100000PF 5% 50V CERAMIC Z5U
C12	420081		10UF 10% 25V TANTALUM
C13	157811		100000PF 5% 50V CERAMIC Z5U
C14	157811		100000PF 5% 50V CERAMIC Z5U
C15	144656		.47UF 20% 16V TANTALUM
C16			680PF 5% 50V CERAMIC
C17	157811		100000PF 5% 50V CERAMIC Z5U
C18	157811		100000PF 5% 50V CERAMIC Z5U
C19	157811		100000PF 5% 50V CERAMIC Z5U
C20	157811		100000PF 5% 50V CERAMIC Z5U
C21	157811		100000PF 5% 50V CERAMIC Z5U
C22	157811		100000PF 5% 50V CERAMIC Z5U
C23	442348		3.3UF 10% 25V TANTALUM
C24	144656		.47UF 20% 16V TANTALUM
C25	157811		100000PF 5% 50V CERAMIC Z5U
C26	462090		200PF 5% 100V CERAMIC NPO
C27			680PF 5% 50V CERAMIC
C28	462071		330PF 1% 50V CERAMIC NPO
C29	157811		100000PF 5% 50V CERAMIC Z5U
C30	157811		100000PF 5% 50V CERAMIC Z5U
C31	157811		100000PF 5% 50V CERAMIC Z5U
C32	157811		100000PF 5% 50V CERAMIC Z5U
C33	462126		33PF 50V CERAMIC NPOTOL+- .5PF
C34	157811		100000PF 5% 50V CERAMIC Z5U
C35	157811		100000PF 5% 50V CERAMIC Z5U
C36	157811		100000PF 5% 50V CERAMIC Z5U
C37	157811		100000PF 5% 50V CERAMIC Z5U
C38	157811		100000PF 5% 50V CERAMIC Z5U
C39	157811		100000PF 5% 50V CERAMIC Z5U
C40	157811		100000PF 5% 50V CERAMIC Z5U
C41	157811		100000PF 5% 50V CERAMIC Z5U
C42	157811		100000PF 5% 50V CERAMIC Z5U
C43	157811		100000PF 5% 50V CERAMIC Z5U
C44	157811		100000PF 5% 50V CERAMIC Z5U
C45	157811		100000PF 5% 50V CERAMIC Z5U

Symbol	Stock No	Drawing No	Description
L13			FERRITE BEAD
L14			FERRITE BEAD
L15			FERRITE BEAD
L16			FERRITE BEAD
P1			HEADER ASSEMBLY 4PIN
P2			6PIN DIN
P3			6PIN DIN
P4			HEADER ASSEMBLY 3PIN
P5			HEADER ASSEMBLY 3PIN
P6			HEADER ASSEMBLY 15PIN
P7			HEADER ASSEMBLY 6PIN
P8			HEADER ASSEMBLY 4PIN
Q1	153567		TRANSISTOR - TYPE 2SA673CD
Q2	742558		TRANSISTOR - TYPE 2SC945RQ
*Q2	147499		TRANSISTOR - TYPE 2SC1815Y
Q3	742558		TRANSISTOR - TYPE 2SC945RQ
*Q3	147499		TRANSISTOR - TYPE 2SC1815Y
Q4	163198		TRANSISTOR - TYPE 2SD467BC
Q7	163198		TRANSISTOR - TYPE 2SD467BC
Q8	745118		TRANSISTOR - TYPE 2SA733P
*Q8	154197		TRANSISTOR - TYPE 2SA1015
Q9	745118		TRANSISTOR - TYPE 2SA733P
*Q9	154197		TRANSISTOR - TYPE 2SA1015
Q10	745118		TRANSISTOR - TYPE 2SA733P
*Q10	154197		TRANSISTOR - TYPE 2SA1015
Q11	745118		TRANSISTOR - TYPE 2SA733P
*Q11	154197		TRANSISTOR - TYPE 2SA1015
R1	442210		330 OHM 1% 1/4W FILM
R3	442196		47 OHM 1% 1/4W FILM
R4	442206		220 OHM 1% 1/4W FILM
R5	442210		330 OHM 1% 1/4W FILM
R6	151316		1000 OHM 1% 1/4W FILM
R7	249262		22000 OHM 2% 1/4W FILM
R8	442202		91 OHM 1% 1/4W FILM
R9	151317		680 OHM 1% 1/4W FILM
R10	249262		22000 OHM 2% 1/4W FILM
R11	151316		1000 OHM 1% 1/4W FILM
R12			9100 OHM 1% 1/4W MF
R13			9100 OHM 1% 1/4W MF
R14	442223		2200 OHM 1% 1/4W FILM
R15	442223		2200 OHM 1% 1/4W FILM
R16	442206		220 OHM 1% 1/4W FILM
R17	442206		220 OHM 1% 1/4W FILM
R18	432572		150 OHM 1% 1/4W FILM
R19	432572		150 OHM 1% 1/4W FILM
R20	442210		330 OHM 1% 1/4W FILM
R21	436170		2000 OHM 1% 1/4W FILM
R22	436170		2000 OHM 1% 1/4W FILM
R23	436170		2000 OHM 1% 1/4W FILM
R24	442214		510 OHM 1% 1/4W FILM

Symbol	Stock No	Drawing No	Description
*UC6	449883		IC - TYPE SN74LS197N
UC7	422257		IC - TYPE SN7402J
UD1	422259		IC - TYPE SN7406J
UD2	442138		IC - TYPE SN74LS164N
UD3	441588		IC - TYPE SN74LS165N
UE2	437738		IC - TYPE SN74LS139
UE3	436511		IC - TYPE SN74LS191N
UE4	451516		IC - TYPE SN74LS74AN
UE5	437780		IC - TYPE SN74LS02N
UE7	433394		IC - TYPE SN74LS193N
UF2	422259		IC - TYPE SN7406J
UF3	436512		IC - TYPE SN74LS10N
UF4	433394		IC - TYPE SN74LS193N
UF5	437989		IC - TYPE SN74LS00N
UF6	451516		IC - TYPE SN74LS74AN
UG2	437719		IC - TYPE 74LS86PC
UG3			IC - TYPE 9602
UG4	432917		IC - TYPE SN7417N
*UG4	422260		IC - TYPE SN7407J
UH4	439284		IC - TYPE LM311N
UH5	432710		IC - TYPE NE592A
UH7	432710		IC - TYPE NE592A
VR1			IC - TYPE VOLT. REG. 12V 1.5A
VR2	430248		IC - TYPE LM340K5.0
VR2	448327		IC - TYPE LM323K
Y1			CRYSTAL 16MHZ
1			SHIELD BOX
2			SHIELD CAP
			PCB ASSEMBLY #1540048
C1	158986		1UF 25V ELECTROLYTIC
C2	152267		47UF 16V ELECTROLYTIC
C3	157811		100000PF 5% 50V CERAMIC Z5U
C4	158986		1UF 25V ELECTROLYTIC
C5	152267		47UF 16V ELECTROLYTIC
C6	157811		100000PF 5% 50V CERAMIC Z5U
C7	157811		100000PF 5% 50V CERAMIC Z5U
C8	157811		100000PF 5% 50V CERAMIC Z5U
C9	157811		100000PF 5% 50V CERAMIC Z5U
C10	157811		100000PF 5% 50V CERAMIC Z5U
C11	423664		1UF 10% 35V TANTALUM
C12	446720		33000PF 10% 25V CERAMIC
C13	160389		220 UF 10V ELECT
C14	157811		100000PF 5% 50V CERAMIC Z5U
C15	420081		10UF 10% 25V TANTALUM
C16	161875		4700 UF 20% 16V ELECT

Symbol	Stock No	Drawing No	Description
L1			COIL - 2.2UH
L2			FERRITE BEAD
L3			FERRITE BEAD
L4			FERRITE BEAD
L5			FERRITE BEAD
L6			FERRITE BEAD
L7			FERRITE BEAD
L8			COIL - 100UH
L9			COIL - 22UH
L10			COIL - 22UH
L11			COIL - 100UH
L12			COIL - 100UH
L13			FERRITE BEAD
L14			FERRITE BEAD
L15			FERRITE BEAD
L16			FERRITE BEAD
P1			HEADER ASSEMBLY 4PIN
P2			6PIN DIN
P3			6PIN DIN
P4			HEADER ASSEMBLY 3PIN
P5			HEADER ASSEMBLY 3PIN
P6			HEADER ASSEMBLY 15PIN
P7			HEADER ASSEMBLY 6PIN
P8			HEADER ASSEMBLY 4PIN
Q1	153567		TRANSISTOR - TYPE 2SA673CD
Q2	742558		TRANSISTOR - TYPE 2SC945RQ
*Q2	147499		TRANSISTOR - TYPE 2SC1815Y
Q3	745118		TRANSISTOR - TYPE 2SA733P
*Q3	154197		TRANSISTOR - TYPE 2SA1015
Q4	745118		TRANSISTOR - TYPE 2SA733P
*Q4	154197		TRANSISTOR - TYPE 2SA1015
Q5	745118		TRANSISTOR - TYPE 2SA733P
*Q5	154197		TRANSISTOR - TYPE 2SA1015
Q6	745118		TRANSISTOR - TYPE 2SA733P
*Q6	154197		TRANSISTOR - TYPE 2SA1015
Q7	742558		TRANSISTOR - TYPE 2SC945RQ
*Q7	147499		TRANSISTOR - TYPE 2SC1815Y
Q8	163198		TRANSISTOR - TYPE 2SD467BC
Q9	163198		TRANSISTOR - TYPE 2SD467BC
Q10	163198		TRANSISTOR - TYPE 2SD467BC
Q11	163198		TRANSISTOR - TYPE 2SD467BC
R1	442196		47 OHM 1% 1/4W FILM
R2	151316		1000 OHM 1% 1/4W FILM
R3	442210		330 OHM 1% 1/4W FILM
R4	442206		220 OHM 1% 1/4W FILM
R5	151316		1000 OHM 1% 1/4W FILM
R6	151316		1000 OHM 1% 1/4W FILM
R7	151316		1000 OHM 1% 1/4W FILM
R8	151316		1000 OHM 1% 1/4W FILM
R9	436170		2000 OHM 1% 1/4W FILM

Symbol	Stock No	Drawing No	Description
UB3			IC - TYPE ROM
UB4			IC - TYPE ROM
UC1			IC - TYPE GATE ARRAY
UC2			IC - TYPE 6522 VIA
UC3			IC - TYPE 6522 VIA
UC4			IC - TYPE 6502 CPU
UC5	436507		IC - TYPE SN74LS04N
*UC5	436444		IC - TYPE SN74LS14N
*UC5	432195		IC - TYPE SN7414N
UC6	437989		IC - TYPE SN74LS00N
UC7	441593		IC - TYPE SN74LS42N
UD1	422259		IC - TYPE SN7406J
UD2	432917		IC - TYPE SN7417N
*UD2	422260		IC - TYPE SN7407J
UD3	437719		IC - TYPE 74LS86PC
UD4			IC - TYPE 9602
UD5	449883		IC - TYPE SN74LS197N
*UD5	442121		IC - TYPE SN74177N
UE4	439284		IC - TYPE LM311N
UE6	433394		IC - TYPE SN74LS193N
UF3	432710		IC - TYPE NE592A
UF4	432710		IC - TYPE NE592A
VR1			IC - TYPE VOLT. REG. 12V 1.5A
VR2	430248		IC - TYPE LM340K5.0
*VR2	448327		IC - TYPE LM323K
Y1			CRYSTAL 16MHZ
1			SHIELD BOX
2			SHIELD CAP
			PCB ASSEMBLY #250442/46
C1	158986		1UF 25V ELECTROLYTIC
C2	152267		47UF 16V ELECTROLYTIC
C3	157811		100000PF 5% 50V CERAMIC Z5U
C4	158486		100 OHM 5% 1/8W FILM
C5	152267		47UF 16V ELECTROLYTIC
C6	157811		100000PF 5% 50V CERAMIC Z5U
C7	157811		100000PF 5% 50V CERAMIC Z5U
C8	157811		100000PF 5% 50V CERAMIC Z5U
C9	157811		100000PF 5% 50V CERAMIC Z5U
C10	157811		100000PF 5% 50V CERAMIC Z5U
C11	423664		1UF 10% 35V TANTALUM
C12	446720		33000PF 10% 25V CERAMIC
C13	160389		220 UF 10V ELECT
C14	157811		100000PF 5% 50V CERAMIC Z5U
C15	420081		10UF 10% 25V TANTALUM
C16	161875		4700 UF 20% 16V ELECT



Symbol	Stock No	Drawing No	Description
L1			COIL - 2.2UH
L2			FERRITE BEAD
L3			FERRITE BEAD
L4			FERRITE BEAD
L5			FERRITE BEAD
L6			FERRITE BEAD
L7			FERRITE BEAD
L8			COIL - 100UH
L9			COIL - 22UH
L10			COIL - 22UH
L11			COIL - 100UH
L12			COIL - 100UH
P1			HEADER ASSEMBLY 4PIN
P2			6PIN DIN
P3			6PIN DIN
P4			HEADER ASSEMBLY 3PIN
P5			HEADER ASSEMBLY 3PIN
P6			HEADER ASSEMBLY 15PIN
P7			HEADER ASSEMBLY 6PIN
P8			HEADER ASSEMBLY 4PIN
Q1	153567		TRANSISTOR - TYPE 2SA673CD
Q2	742558		TRANSISTOR - TYPE 2SC945RQ
*Q2	147499		TRANSISTOR - TYPE 2SC1815Y
Q3	745118		TRANSISTOR - TYPE 2SA733P
*Q3	154197		TRANSISTOR - TYPE 2SA1015
Q4	745118		TRANSISTOR - TYPE 2SA733P
*Q4	154197		TRANSISTOR - TYPE 2SA1015
Q5	745118		TRANSISTOR - TYPE 2SA733P
*Q5	154197		TRANSISTOR - TYPE 2SA1015
Q6	745118		TRANSISTOR - TYPE 2SA733P
*Q6	154197		TRANSISTOR - TYPE 2SA1015
Q7	742558		TRANSISTOR - TYPE 2SC945RQ
*Q7	147499		TRANSISTOR - TYPE 2SC1815Y
Q8	163198		TRANSISTOR - TYPE 2SD467BC
Q9	163198		TRANSISTOR - TYPE 2SD467BC
Q10	163198		TRANSISTOR - TYPE 2SD467BC
Q11	163198		TRANSISTOR - TYPE 2SD467BC
R1	442196		47 OHM 1% 1/4W FILM
R2	151316		1000 OHM 1% 1/4W FILM
R3	442210		330 OHM 1% 1/4W FILM
R4	442206		220 OHM 1% 1/4W FILM
R5	151316		1000 OHM 1% 1/4W FILM
R6	151316		1000 OHM 1% 1/4W FILM
R7	151316		1000 OHM 1% 1/4W FILM
R8	151316		1000 OHM 1% 1/4W FILM
R9	436170		2000 OHM 1% 1/4W FILM
R10	436170		2000 OHM 1% 1/4W FILM
R11	442232		5100 OHM 1% 1/4W FILM
R12	249262		22000 OHM 2% 1/4W FILM
R12	151289		15000 OHM 1% 1/4W FILM

Symbol	Stock No	Drawing No	Description
UC3			IC - TYPE 6522 VIA
UC4			IC - TYPE 6502 CPU
UC5	436507		IC - TYPE SN74LS04N
*UC5	436444		IC - TYPE SN74LS14N
*UC5	432195		IC - TYPE SN7414N
UC7	437989		IC - TYPE SN74LS00N
UC8	441593		IC - TYPE SN74LS42N
UD1	422259		IC - TYPE SN7406J
*UD1	422259		IC - TYPE SN7406J
UD2	432917		IC - TYPE SN7417N
*UD2	422260		IC - TYPE SN7407J
UD3	437719		IC - TYPE 74LS86PC
UD4	437992		IC - TYPE SN74LS123N
UD5	449883		IC - TYPE SN74LS197N
*UD5	442121		IC - TYPE SN74177N
UE4	439284		IC - TYPE LM311N
UE6	433394		IC - TYPE SN74LS193N
UF3	432710		IC - TYPE NE592A
UF4	432710		IC - TYPE NE592A
VR1			IC - TYPE VOLT. REG. 12V 1.5A
VR2	430248		IC - TYPE LM340K5.0
*VR2	448327		IC - TYPE LM323K
Y1			CRYSTAL 16MHZ

ALL SYMBOL NUMBERS PREFACED BY  
AN ASTERISK (\*) ARE SUBSTITUTES